


Argonne

TRANSISTOR TRANSFORMERS

LIST PRICE 5.00 ANY TYPE




CHOOSE FROM 77 TYPES — THE ONLY COMPLETE LINE OF QUALITY TRANSISTOR TRANSFORMERS
 • NICKEL-STEEL LAMINATIONS • WOUND ON NYLON BOBBINS • MYLAR OUTER WRAP • COLOR CODED LEADS
 Efficiently designed to meet the needs of miniaturization and engineered to provide more power handling capacity and improved frequency response with minimum distortion. All are nickel-steel laminations. Applications under "TYPE" column shows typical use. Many units may be used for other applications as well. Average net weight 1 1/4 oz.; average shp. wt., 4 oz. **MADE IN U.S.A.**

ARGONNE NUMBER	TYPE	IMPEDANCE PRIMARY OHMS	IMPEDANCE SECONDARY OHMS	UNBALANCED CURRENT PRI. D.C. MA	POWER MILLI-WATTS	D.C. RESISTANCE PRI. OHMS	D.C. RESISTANCE SEC. OHMS	OVERALL SIZE
AR-141	Input	500,000	1,500 CT	.3	350	3500	60	1" x 3/4" x 3/4"
AR-142	Input	500,000	200 CT	.3	350	3500	20	1" x 3/4" x 3/4"
AR-143	Input	250,000	200 CT	.5	350	3500	20	1" x 3/4" x 3/4"
AR-144	Input	200,000	1,500 CT	.5	350	3000	65	1" x 3/4" x 3/4"
AR-100	Input	200,000	1,000	.5	100	3600	90	1" x 3/4" x 3/4"
AR-126	Input	150,000	1,500 CT	2.	100	3700	55	1" x 3/4" x 3/4"
AR-101	Input	100,000	3,000 CT	.5	100	3600	60	1" x 3/4" x 3/4"
AR-145	Input	100,000	2,000 CT	.5	350	3000	50	1" x 3/4" x 3/4"
AR-102	Input	100,000	1,500 CT	.5	100	3600	40	1" x 3/4" x 3/4"
AR-146	Input	100,000	50	.5	350	3000	1.6	1" x 3/4" x 3/4"
AR-127	Input	50,000	3,000 CT	1.	100	2000	50	1" x 3/4" x 3/4"
AR-128	Input	50,000	1,500 CT	2.	100	3000	50	1" x 3/4" x 3/4"
AR-129	Input	50,000	1,000	2.	100	2500	20	1" x 3/4" x 3/4"
AR-148	Input	50,000	500 CT	1.	175	1300	20	3/4" x 3/8" x 3/8"
AR-149	Input	50,000	200 CT	1.	175	1300	10	3/4" x 3/8" x 3/8"
AR-147	Input	50,000	.30 CT	1.	175	1300	1.5	3/4" x 3/8" x 3/8"
AR-150	Input	40,000	100	1.	175	850	6	3/4" x 3/8" x 3/8"
AR-103	Driver	20,000	2,000 CT	1.	100	400	50	1" x 3/4" x 3/4"
AR-104	Driver	20,000	1,000	1.	100	400	50	3/4" x 3/8" x 3/8"
AR-151	Driver	20,000	800 CT	1.5	175	600	60	3/4" x 3/8" x 3/8"
AR-105	Driver	20,000	400	1.	100	600	30	1" x 3/4" x 3/4"
AR-130	Output	20,000	8	.5	100	400	0.6	3/4" x 3/8" x 3/8"
AR-131	Output	20,000	3.2	.5	100	400	0.3	3/4" x 3/8" x 3/8"
AR-106	Driver	16,000	4,000	1.	100	620	350	3/4" x 3/8" x 3/8"
AR-152	Driver	15,000	200 CT	1.5	175	550	10	3/4" x 3/8" x 3/8"
AR-107	Driver	15,000	200	1.5	250	1000	20	1" x 3/4" x 3/4"
AR-108	Driver	10,000	3,000 CT	1.5	100	200	100	3/4" x 3/8" x 3/8"
AR-109	Driver	10,000	2,000 CT	1.5	100	500	50	3/4" x 3/8" x 3/8"
AR-153	Driver	10,000	200 CT	2.	175	400	10	3/4" x 3/8" x 3/8"
AR-110	Output	10,000	16	2.	150	600	2.5	3/4" x 3/8" x 3/8"
AR-132	Output	10,000	8	1.	100	600	.6	3/4" x 3/8" x 3/8"
AR-133	Output	10,000	3.2	1.	100	600	.3	3/4" x 3/8" x 3/8"
AR-158	Input	5,000 CT	80,000	2.	175	350	1800	3/4" x 3/8" x 3/8"
AR-157	Input	5,000	45,000	2.	175	250	1600	3/4" x 3/8" x 3/8"
AR-156	Input	5,000	30,000	2.	175	150	1300	3/4" x 3/8" x 3/8"
AR-155	Input	5,000	10,000	2.	175	150	450	3/4" x 3/8" x 3/8"
AR-154	Input	5,000 CT	7,500 CT	2.	175	150	400	3/4" x 3/8" x 3/8"
AR-173	Driver	5,000	3,000 CT	2.	350	200	90	1" x 3/4" x 3/4"
AR-111	Output	5,000	100	1.	100	600	10	3/4" x 3/8" x 3/8"
AR-134	Output	4,000 CT	8	4.	250	150	.8	1" x 3/4" x 3/4"
AR-135	Output	4,000 CT	3.2	4.	250	150	.3	1" x 3/4" x 3/4"
AR-112	Output	3,500	200	1.	150	120	25	1" x 3/4" x 3/4"
AR-113	Driver	3,000 CT	1,000	9.	150	100	60	3/4" x 3/8" x 3/8"
AR-114	Output	2,500	11	10.	150	50	1.1	3/4" x 3/8" x 3/8"
AR-115	Input	2,000 CT	8,000 CT	2.	150	150	660	1" x 3/4" x 3/4"
AR-116	Output	2,000	200	4.	250	120	20	1" x 3/4" x 3/4"
AR-175	Driver	2,000	1,500 CT	3.	350	150	60	1" x 3/4" x 3/4"
AR-159	Driver	1,500	500 CT	4.	175	100	20	3/4" x 3/8" x 3/8"
AR-136	Output	1,000 CT	100	4.	250	120	10	1" x 3/4" x 3/4"
AR-137	Output	1,000 CT	8	4.	250	120	.9	1" x 3/4" x 3/4"
AR-138	Output	1,000 CT	3.2	4.	250	120	.3	1" x 3/4" x 3/4"
AR-160	Output	800 CT	3.2	5.	175	40	.3	3/4" x 3/8" x 3/8"
AR-161	Output	650 CT	16	5.	175	27	1.3	3/4" x 3/8" x 3/8"
AR-162	Output	500 CT	500 CT	5.	350	18	18	1" x 3/4" x 3/4"
AR-163	Output	500 CT	150 CT	5.	175	18	8	3/4" x 3/8" x 3/8"
AR-165	Output	500 CT	50	5.	175	18	4	3/4" x 3/8" x 3/8"
AR-117	Output	500 CT	30	5.	100	20	1.5	3/4" x 3/8" x 3/8"
AR-118	Output	500 CT	16	5.	100	20	1.5	3/4" x 3/8" x 3/8"
AR-164	Output	500 CT	8	5.	175	18	.8	3/4" x 3/8" x 3/8"
AR-119	Output	500 CT	3.2	5.	100	20	.3	3/4" x 3/8" x 3/8"
AR-166	Output	400 CT	16	5.	175	16	1.3	3/4" x 3/8" x 3/8"
AR-120	Output	400 CT	11	1.	150	20	.9	3/4" x 3/8" x 3/8"
AR-167	Output	400 CT	8 or 3.2	5.	175	16	6.3	3/4" x 3/8" x 3/8"
AR-168	Output	300 CT	16	6.	175	12	1.4	3/4" x 3/8" x 3/8"
AR-121	Output	300 CT	3.2	6.	150	20	.25	3/4" x 3/8" x 3/8"
AR-139	Output	250 CT	8	2.	250	15	.7	1" x 3/4" x 3/4"
AR-122	Output	250 CT	3.2	2.	150	11	.3	1" x 3/4" x 3/4"
AR-123	Input	200	2,000 CT	2.	150	11	50	1" x 3/4" x 3/4"
AR-124	Output	200 CT	16	2.	250	20	1.3	3/4" x 3/8" x 3/8"
AR-169	Output	200 CT	8 or 3.2	7.	175	9	6.3	3/4" x 3/8" x 3/8"
AR-140	Output	200 CT	3.2	2.	100	10	.3	3/4" x 3/8" x 3/8"
AR-170	Output	160 CT	8 or 3.2	8.	350	10	6.3	1" x 3/4" x 3/4"
AR-176	Output	125 CT	8	8.	350	4	.7	1" x 3/4" x 3/4"
AR-174	Output	125 CT	3.2	8.	350	6	.3	1" x 3/4" x 3/4"
AR-171	Output	100 CT	10 CT	10.	175	4	.8	3/4" x 3/8" x 3/8"
AR-172	Output	48 CT	8 or 3.2	15.	350	2.3	6.3	1" x 3/4" x 3/4"
AR-125	Input	3	4,000	15.	250	14	50	3/4" x 3/8" x 3/8"



HIGH FIDELITY TRANSISTOR TRANSFORMERS
 Driver and output transformers, completely encased. Response 20-20,000 cps ± 0.25 db. Output transformer 1.5 watts out 20-20,000 cps ± 2 db. Size 1-5/16" x 1-5/16" x 1 1/4". Shpg. wt., 9 oz.
MODEL AR-500 DRIVER TRANSFORMER: 5000 ohm primary, 3000 ohm CT secondary; dc resistance of primary 50 ohms, secondary 75 ohms; unbalanced primary dc current 20 ma. List Price 9.60
MODEL AR-501 OUTPUT TRANSFORMER: Primary 125 ohms CT, secondary 8 ohms; primary dc resistance 4 ohms, secondary 0.8; unbalanced primary current 50 ma. dc. List Price 9.60



HIGH POWER TRANSISTOR AUDIOS
 For the new high-output transistors
MODEL AR-503 OUTPUT TRANSFORMER: 6 watts. 70-20,000 cps ± 2 db. Primary 48 ohms CT, secondary 3.2 ohms; primary dc resistance 1.1 ohms, secondary 0.3; unbalanced primary current 200 ma. dc. Size 1-9/16" x 1 1/8" x 1-9/16". Shpg. wt., 1 lb. List Price 2.95
MODEL AR-504 INPUT TRANSFORMER: 2 watts. 70-20,000 cps ± 2 db. Primary 100 ohms, secondary 200 ohms CT. Primary dc resistance 1.8 ohms, secondary 2.7; unbalanced primary current 200 ma. dc. List Price 2.50

Argonne

Write to Factory For Complete Catalog Of Audio & Miniaturization Products
ELECTRONICS MFG. CORP. - JAMAICA 33, N. Y.
 MANUFACTURERS & IMPORTERS