



LYNX: MALE 50 PIN 'D'
CONN A

- 1 GND
- 2 C.V. GND SENSE
- 3 STOP
- 6 "LIFTER DEFEAT"
- 7 FAST FWD
- 8 RECORD TALLY
- 9 SPARE INPUT
- 10 REMOTE LOCK LIGHT
- 11 A1 REC ENABLE
- 12 "REHEARSE"
- 14 SERVO RELAY COM
- 15 SERVO RELAY N/O
- 18 +5V
- 19 EDIT STOP
- 20 SEARCH
- 23 CTRL COM
- 24 REWIND
- 25 PLAY TALLY
- 26 DIRECTION
- 27 "A2 REC ENABLE"
- 28 VID REC ENABLE
- 31 SERVO RELAY N/C
- 34 GND
- 35 RECORD STOP COM
- 36 SEARCH COM
- 37 PLAY
- 39 CAPSTAN CTRL VOLT
- 40 RECORD
- 41 SPARE INPUT
- 42 TACH
- 46 MUTE RELAY N/O
- 47 MUTE RELAY N/C
- 48 MUTE RELAY COM

JVC: MALE 45 PIN HIROSE
CONN B ("REMOTE")

- 1 GND
- 2 RECORD CMD
- 3 STOP CMD
- 4 PLAY CMD
- 5 FAST FWD CMD
- 6 REWIND CMD
- 7 FWD SEARCH SEL
- 8 SEARCH CMD
- 9 REV SEARCH SEL
- 10 STILL CMD
- 11 PREROLL CMD
- 12 EDIT START CMD
- 13 EDIT STOP CMD
- 21 SEARCH SPD (TO TRANS)
- 22 EDIT TALLY
- 23 STILL TALLY
- 24 SEARCH TALLY
- 25 PREROLL TALLY
- 26 FAST FWD TALLY
- 27 PLAY TALLY
- 28 STOP TALLY
- 29 REWIND TALLY
- 30 RECORD TALLY
- 31 TAPE DIR
- 34 +12 VOLTS DC
- 35 CAPSTAN F.S
- 37 "FASTER" CMD
- 38 -SPARE-
- 39 "SLOWER" CMD
- 42 CAPSTAN TSO CMD
- 44 AUDIO DUB TALLY

JVC: FEMALE 45 PIN HIROSE
CONN C (TO REMOTE CTL)

- 1 GND
- 2 RECORD CMD
- 3 STOP CMD
- 4 PLAY CMD
- 5 FAST FWD CMD
- 6 REWIND CMD
- 7 FWD SEARCH SEL
- 8 SEARCH CMD
- 9 REV SEARCH SEL
- 10 STILL CMD
- 11 PREROLL CMD
- 12 EDIT START CMD
- 21 SEARCH SPD (FROM REMOTE)
- 22 EDIT TALLY
- 23 STILL TALLY
- 24 SEARCH TALLY
- 25 PREROLL TALLY
- 26 FAST FWD TALLY
- 27 PLAY TALLY
- 28 STOP TALLY
- 29 REWIND TALLY
- 30 RECORD TALLY
- 31 TAPE DIR
- 34 +12 VOLTS DC
- 35 CAPSTAN F.S
- 38 -SPARE-
- 44 AUDIO DUB TALLY

REV	DESCRIPTION
00A 10/18/88 AD	ORIGINAL RELEASE.
0 1/2/90 BT	ADDED PLAY TALLY. MOVED 12V TO RED/BRN MOVED PULLUPS TO CONN C. CHANGED DWS. #. WAS 30-0005-00A

(C) 1989 TIMELINE, INC. 270 Lafayette St. New York, N.Y. 10012		APP'D MC
SCHEMATIC CABLE ASSEMBLY JVC TYPE A		CHK'D [Signature]
CONFIDENTIAL	DATE	1/2/90
DWS	REV	PAGE
700019-20	D	1
		SIZE B